

## DESCRIPTION

PT2262 is a remote control encoder paired with PT2272 utilizing CMOS Technology. It encodes data and address pins into a serial coded waveform suitable for RF or IR modulation. PT2262 has a maximum of 12 bits of tri-state address pins providing up to 531.441 (or 312) address codes; thereby, drastically reducing any code collision and unauthorized code scanning possibilities.


## APPLICATIONS

- Car Security System •
- Garage Door Controller •
- **Remote Control Fan** •
- Home Security/Automation System •
- Remote Control Toys •
- Remote Control for Industrial Use

## **BLOCK DIAGRAM**

### FEATURES

- CMOS Technology
- Low Power Consumption
- Verv High Noise Immunity
- Up to 12 Tri-State Code Address Pins •
- Up to 6 Data Pins •
- Wide Range of Operating Voltage: Vcc = 4 ~ 15V
- Single Resistor Oscillator •
- Latch or Momentary Output Type
- Available in DIP and SOP




Tel: 886-66296288 • Fax: 886-29174598 • http://www.princeton.com.tw • 2F, 233-1, Baociao Road, Sindian, Taipei 23145, Taiwan




## **APPLICATION CIRCUITS**

#### **UHF BAND 4 DATA TRANSMITTER CIRCUIT IS RECOMMENDED**






# UHF BAND ADDRESS-ONLY (ZERO DATA) TRANSMITTER CIRCUIT IS RECOMMENDED






### UHF BAND ADDRESS-ONLY (ZERO DATA) ZERO-STAND-BY TRANSMITTER CIRCUIT IS RECOMMENDED.



### INFRARED RAY 6-DATA CIRCUIT. ADJUST ROSC TO GET 38KHZ CARRIER PULSE AT DOUT PIN IS RECOMMENDED.






## **ORDERING INFORMATION**

| Valid Part Number | Package Type         | Top ode    |
|-------------------|----------------------|------------|
| PT2262            | 18 Pins, DIP, 300mil | PT2262     |
| PT2262-S18        | 18 Pins, SOP, 300mil | PT2262-S18 |
| PT2262-S          | 20 Pins, SOP, 300mil | PT2262-S   |
| PT2262-IRS        | 20 Pins, SOP, 300mil | PT2262-IRS |

## **PIN CONFIGURATION**



### **PIN DESCRIPTION**

| Din Nama                       | I/O |   | Pin No.  |                 |                 |  |  |  |
|--------------------------------|-----|---|--|-----------------|-----------------|--|--|--|
| Pin Name                       | 10  | and the second  | 18 Pins  | 20 Pins         |                 |  |  |  |
| A0 ~ A5                        | -   | Code Address Pin Nos<br>These six tri-state pins<br>encoded waveform bit<br>(floating). | 1~6  | 1 ~ 6           |                 |  |  |  |
| A6/D5, A7/D4<br>A8/D3 ~ A11/D0 | 0-0 | These six tri-state pins<br>encoded waveform bit<br>address pins, they car              | <ul> <li>s.6 ~ 11/Data Pin Nos.5 ~ 0.</li> <li>s are detected by PT2262 to determine the</li> <li>6 ~ bit 11. When these pins are used as</li> <li>b e set to "0", "1", or "f" (floating). When these pins, they can be set only to "0" or "1".</li> </ul> | 7, 8<br>10 ~ 13 | 7, 8<br>12 ~ 15 |  |  |  |
| /TE                            | 1   |   | Transmission Enable.<br>Active Low Signal. PT2262 outputs the encoded waveform to DOUT when this pin is pulled to low.   |                 |                 |  |  |  |
| OSC1                           | 0   | Oscillator Pin No.1   | A resistor connected between these two pins determine the fundamental frequency of the   | 15              | 17              |  |  |  |
| OSC2                           | Ι   | Oscillator Pin No.2   | PT2262.  | 16              | 18              |  |  |  |
| DOUT                           | 0   |   | m is serially outputted to this pin. When PT2262<br>OUT outputs low (Vss) voltage.   | 17              | 19              |  |  |  |
| Vcc                            | -   | Positive Power Supply   | /  | 18              | 20              |  |  |  |
| Vss                            | -   | Negative Power Supp   | ly   | 9               | 9               |  |  |  |



## **FUNCTIONAL DESCRIPTION**

PT2262 encodes the code address and data set at A0 ~ A5 and A6/D5 ~ A11/D0 into a special waveform and outputs it to the DOUT when TE is pulled to "0" (Low State). This waveform is fed to either the RF modulator or the IR transmitter for transmission. The transmitted radio frequency or infrared ray is received by the RF demodulator or IR receiver and reshaped to the special waveform. PT2272 is then used to decode the waveform and set the corresponding output pin(s). Thus completing a remote control encoding and decoding function.


### **RF OPERATION**

#### CODE BITS

A Code Bit is the basic component of the encoded waveform, and can be classified as either an AD (Address/Data) Bit or a SYNC (Synchronous) Bit.

#### ADDRESS/DATA (AD) BIT WAVEFORM


An AD Bit can be designated as Bit "0", "1" or "f" if it is in low, high or floating state respectively. One bit waveform consists of 2 pulse cycles. Each pulse cycle has 16 oscillating time periods. For further details, please refer to the diagram below:



#### SYNCHRONOUS (SYNC.) BIT WAVEFORM

Published by WWW.SKYTECH.ir

The Synchronous Bit Waveform is 4 bits long with 1/8 bit width pulse. Please refer to the diagram below:



#### **CODE WORD**

A group of Code Bits is called a Code Word. A Code Word consists of 12 AD bits followed by one Sync Bit. The 12 AD bits are determined by the corresponding states of A0 ~ A5 and A6/D5 ~ A11/D0 pins at the time of transmission. When Data Type of PT2262 is used, the address bits will decrease accordingly.

For example: In the 3 Data Type where the address has nine (9) bits, the transmitting format is:

|  | 9 Address Bits | 3 Data Bits | Sync. bit |  |
|--|----------------|-------------|-----------|--|
|--|----------------|-------------|-----------|--|

PT2262 / PT2272 has a maximum of twelve (12) Address Bits including the six (6) Address/Data bits. The following diagram shows the code bits with their corresponding pins.

|         | A0 | A1   | A    | 2    | A3   | A4  | A  | 5              | A6/ | D5  | A7/  | ′D4   | A8/D3    | A9/D2 | A10/D1 | A11/D0 | SYNC. Bit |
|---------|----|------|------|------|------|-----|----|----------------|-----|-----|------|-------|----------|-------|--------|--------|-----------|
| •       |    |      |      |      |      |     |    |                |     |     |      |       |          |       |        |        |           |
| I       |    |      |      |      |      |     |    |                |     | One | Corr | nlete | Code Wo  | ord   |        |        |           |
|         |    |      |      |      |      | • - |    | ۸ <del>.</del> |     |     |      | •     |          |       |        |        |           |
| 0 Data: |    |      |      |      |      |     |    |                |     |     |      |       | Sync Bit |       |        |        |           |
| 1 Data: |    | A0 A | 1 A2 | 2 A3 | 6 A4 | A5  | A6 | A7             | A8  | A9  | A10  | D0    | Sync Bit |       |        |        |           |
| 2 Data  |    | A0 A | 1 A2 | 2 A3 | 6 A4 | A5  | A6 | A7             | A8  | A9  | D1   | D0    | Sync.Bit |       |        |        |           |
| 3 Data  |    | A0 A | 1 A2 | 2 A3 | 6 A4 | A5  | A6 | A7             | A8  | D2  | D1   | D0    | Sync.Bit |       |        |        |           |
| 4 Data  |    | A0 A | 1 A2 | 2 A3 | A4   | A5  | A6 | Α7             | D3  | D2  | D1   | D0    | Sync.Bit |       |        |        |           |

The Code Bits A0 ~ A5 and A6/D5 ~ A11/D0 are determined by the states of A0 ~ A5 and A6/D5 ~ A11/D0 pins. For example, when the A0 (Pin No. 1) is set to "1" (Vcc), the Code Bit A0 is synthesized as "1" bit. In the same manner, when it (A0 Pin) is set to "0" (Vss) or left floating, the Code Bit A0 is synthesized as a "0" or "f" bit respectively.

D0

D0

Sync.Bit

Sync.Bit

#### CODE FRAME

5 Data

6 Data

A Code Frame consists of four (4) continuous Code Words. When PT2262 detects "0" on the /TE (meaning, the /TE is active "low"), it outputs a Code Frame at DOUT. If /TE is still active at the time the Code Frame transmission ends, T2262 outputs another Code Frame. It should be noted that the Code Frame is synthesized at the time of transmission.




#### SIGNAL RESISTOR OSCILLATOR

A0 A1 A2 A3 A4 A5 A6 D4 D3 D2 D1

A0 A1 A2 A3 A4 A5 D5 D4 D3 D2 D1

The built-in oscillator circuitry of PT2262 allows a precision oscillator to be constructed by connecting an external resistor between OSC1 and OSC2 pins. For PT2272 to decode correctly the received waveform, the oscillator frequency of PT2272 must be 2.5 ~ 8 times that of transmitting PT2262. The typical oscillator frequency with various resistor values for both PT2262 and PT2272 are shown below:



Suggested oscillator resistor values are shown below

Published by WWW.SKYTECH.ir

| PT2262 | PT2272  |
|--------|---------|
| 4.7 M  | 820 K*  |
| 3.3 M  | 680 K*  |
| 1.2 M  | 200 K** |
| 1.2 M  | 200 K** |

Note:

-- Operates when PT2272's Vcc=5V to 15V

-- Operates when PT2272's Vcc=3V to 15V

This means that if PT2272 supply voltage is lower than 5V, you need to use a lower oscillator resistor value for both PT2262 and PT2272.

V4.0




### IR OPERATION

In the IR Type of Operation, the functions are similar to the above descriptions except for the output waveform that has a carrier frequency of 38KHz. Details are as follows:

#### CODE BITS

The Code Bits are further modulated with a 38KHz carrier frequency and can be "0", "1" or "f" bit. Their waveforms are shown in the diagram below.



#### CODE WORD

A Code Word is made up of code bits and the format is the same as that of the RF Code Word.


#### CODE FRAME

Likewise, a Code Frame is made up of Code Words and the format is the same as that of RF Type of Operation.

#### OSCILLATOR

The Oscillator Frequency for the IR Type of Operation is twice the carrier frequency. Thus, the oscillator frequency should be kept at 76 KHz. A  $430K \sim 560K\Omega$  oscillator resistor between OSC 1 and OSC 2 pins is recommended. It should be noted that the carrier is a 50% duty cycle frequency.

#### **OPERATION FLOW CHART**





## **ABSOLUTE MAXIMUM RATING**

| Parameter                 | Symbol | Condition | Rating         | Unit |
|---------------------------|--------|-----------|----------------|------|
| Supply Voltage            | Vcc    |           | -0.3 ~ 16.0    | V    |
| Input Voltage             | VI     |           | -0.3 ~ Vcc+0.3 | V    |
| Output Voltage            | VO     |           | -0.3 ~ Vcc+0.3 | V    |
| Maximum Power Dissipation | Pa     | Vcc = 12V | 300            | mW   |
| Operating Temperature     | Topr   |           | -40 ~ +85      | °C   |
| Storage Temperature       | Tstg   |           | -65 ~ 150      | °C   |

## **DC ELECTRICAL CHARACTERISTICS**

| Parameter                   | Symbol | Test Condition                           | Min. | Тур. | Max. | Unit |
|-----------------------------|--------|--|------|------|------|------|
| Supply Voltage              | Vcc    |  | 4    |      | 15   | V    |
| Stand-by Current            | ISB    | Vcc = 12V<br>OSC2 = 12V<br>A0 ~ A11 Open |      | 0.1  | 1    | μΑ   |
|                             |        | Vcc = 5V, VOH = 3V                       | -3   |      |      | mA   |
| DOUT Output Driving Current | IOH    | Vcc = 8V, VOH = 4V                       | -6   |      |      | mA   |
|                             |        | Vcc = 12V, VOH = 6V                      | -10  |      |      | mA   |
|                             |        | Vcc = 5V, VOL=3V                         | 2    |      |      | mA   |
| DOUT Output Sinking Current | IOL    | Vcc = 8V, VOL = 4V                       | 5    |      |      | mA   |
|                             |        | Vcc = 12V, VOL = 6V                      | 9    |      |      | mA   |




ELECTRONIC



PT2262

## **PACKAGE INFORMATION**

### 18 PINS, DIP, 300MIL




Notes: 1. Refer to JEDEC MS-001 AC 2. Unit: mm

V4.0



PT2262

## 18 PINS, SOP, 300MIL



Notes:


1. Refer to JEDEC MS-013 AB

2. Unit: mm



**PT2262** 

### 20 PINS, SOP, 300 MIL



Notes:

2. Unit: mm



#### **IMPORTANT NOTICE**

Princeton Technology Corporation (PTC) reserves the right to make corrections, modifications, enhancements, improvements, and other changes to its products and to discontinue any product without notice at any time. PTC cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a PTC product. No circuit patent licenses are implied.

Princeton Technology Corp. 2F, 233-1, Baociao Road, Sindian, Taipei 23145, Taiwan Tel: 886-2-66296288 Fax: 886-2-29174598 http://www.princeton.com.tw

